

DESCRIPTION

The **CBS ArcSafe® RSA-162** remote switch actuator (RSA) is designed to operate the General Electric EntelliGuard G circuit breaker without having to make any modifications to existing electrical equipment thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-162 allows technicians to remotely charge, close, or trip the circuit breaker from a safe distance of up to 300 feet while remaining stationed outside the arc-flash boundary. Designed, manufactured, and assembled in the USA, all RSA units are portable, fast, and easy to set up, offer mechanical and/or electrical safety protection, are adjustable to fit unique electrical equipment configurations, reduce the requirements for personal protection equipment (PPE), and help customers with NFPA 70E arc-flash safety compliance. Optional features include radio remote with range up to 300 feet, 24 V DC LED light, wireless video camera system with LCD monitor, and rugged protective case assembly.

SPECIFICATIONS

| | |
|-----------------------|---|
| WEIGHT: | 25.5 lbs |
| DIMENSIONS: | 18.53"H x 19.20"W x 6.27"D |
| POWER CONSUMPTION: | 50W |
| OPERATING DISTANCE: | 25-300 feet |
| COMPATIBILITY: | GG/GJ/GH/GK-04/07/08/10/13/16/20/ 25/32/40/50/64 circuit breakers with ratings from 400-6000A |
| CONTROL/POWER SOURCE: | CBS ArcSafe® RSO-IIID control console |

OVERVIEW

- Remote operation from up to 300 feet
- Lightweight, portable, and adjustable
- Simple setup; no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

