



#### DESCRIPTION

The **CBS ArcSafe® RSA-187A** remote switch actuator is designed to remotely close and open all sizes of the General Electric "E Line" (150A frame size) of low-voltage molded case circuit breakers. The RSA-187A allows personnel to operate the molded case circuit breaker from a safe distance stationed outside the arc-flash perimeter without having to make any modifications to the breaker. Capable of operation from up to 300 feet away, this custom-built actuator can reduce or eliminate the need for bulky and expensive arc-flash hazard suits. Designed, manufactured, and assembled in the U.S., this actuator is lightweight and portable, allowing for simple installation and operation in even the hardest-to-access areas.

#### SPECIFICATIONS

WEIGHT:	6.8 lbs
DIMENSIONS:	5.6"H x 8.0"W x 5.6"D
POWER CONSUMPTION:	30W
OPERATING DISTANCE:	25-300 feet
COMPATIBILITY:	General Electric "E Line" Low-Voltage Molded Case Circuit Breaker – 150A Frame Size, Flush Mounted (Compatible With Type TE/TEB/TEC/TECL/TED/TEML/THED Breakers)
CONTROL/POWER SOURCE:	CBS ArcSafe® RSO-I AR control console

#### OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Quick installation and removal from gear
- Adjustable travel and locators to accommodate entire product line
- Reduces or eliminates need for arc-flash hazard suits
- Eliminates all hazardous manual contact with gear during operation
- Designed, manufactured, and assembled in the USA

