



### DESCRIPTION

The **CBS ArcSafe® RSA-39B** remote switch actuator (RSA) is designed to operate the General Electric (GE) E9000 Evolution motor control center (MCC) main switch without having to make any modifications to existing electrical equipment thanks to CBS ArcSafe's magnetic latching system. The lightweight, portable RSA-39B allows technicians to remotely close or trip the circuit breaker from a safe distance of up to 300 feet while remaining stationed outside the arc-flash boundary. The RSA-39B is compatible with GE E9000 Evolution MCC main units. Typical applications include commercial, industrial, and service entrance applications to protect and switch main, feeders, and incoming lines. Designed, manufactured, and assembled in the USA, all RSA units are portable, fast, and easy to set up, offer mechanical and/or electrical safety protection, are adjustable to fit unique electrical equipment configurations, reduce the requirements for personal protection equipment (PPE), and help customers with NFPA 70E arc-flash safety compliance. Optional features include radio remote with range up to 300 feet, 24 V DC LED light, wireless video camera system with LCD monitor, and rugged protective case assembly.

### SPECIFICATIONS

|                       |                                     |
|-----------------------|-------------------------------------|
| WEIGHT:               | 14 lbs                              |
| DIMENSIONS:           | 15.5" W x 19.5" H x 10.7" D         |
| POWER CONSUMPTION:    | 30W                                 |
| OPERATING DISTANCE:   | 25-300 feet                         |
| COMPATIBILITY:        | GE E9000 Evolution MCC main units   |
| CONTROL/POWER SOURCE: | CBS ArcSafe® RSO-IV Control Console |

### OVERVIEW

- Remote operation from up to 300 feet away
- Lightweight and portable for hard-to-access areas
- Simple setup, no equipment modification required
- Reduces or eliminates need for arc-flash hazard suits
- Designed, manufactured, and assembled in the USA

